

Permutation-invariant codes encoding more than one qubit

Yingkai Ouyang

*Singapore University of Technology and Design, 8 Somapah Road, Singapore**

Joseph Fitzsimons

Singapore University of Technology and Design, 8 Somapah Road, Singapore and
Centre for Quantum Technologies, National University of Singapore, 3 Science Drive 2, Singapore*

A permutation-invariant code on m qubits is a subspace of the symmetric subspace of the m qubits. We derive permutation-invariant codes that can encode an increasing amount of quantum information while suppressing leading order spontaneous decay errors. To prove the result, we use elementary number theory with prior theory on permutation invariant codes and quantum error correction.

The promise offered by the fields of quantum cryptography [1, 2] and quantum computation [3] has fueled recent interest in quantum technologies. To implement such technologies, one needs a way to reliably transmit quantum information, which is inherently fragile and often decoheres because of unwanted physical interactions. If a decoherence-free subspace (DFS) [4] of such interactions were to exist, encoding within it would guarantee the integrity of the quantum information. Indeed, in the case of the spurious exchange couplings [5], the corresponding DFS is just the symmetric subspace of the underlying qubits. In practice, only approximate DFSs are accessible because of small unpredictable perturbations to the dominant physical interaction [6], and using approximate DFSs necessitate a small amount of error correction. When the approximate DFS is the symmetric subspace, permutation-invariant codes can be used to negate the aforementioned errors [7–9]. However, as far as we know, all previous permutation-invariant codes encode only one logical qubit [7–9]. One may then wonder if there exist permutation-invariant codes that can encode strictly more quantum information than a single qubit whilst retaining some capability to be error-corrected.

The first example of a permutation-invariant code which encodes one qubit into 9-qubits while being able to correct any single qubit error was given by Ruskai over a decade ago [7]. A few years later, Ruskai and Pollatshek found 7-qubit permutation invariant codes encoding a single qubit which correct arbitrary single qubit errors [8]. Recently permutation-invariant codes encoding a single qubit into $(2t + 1)^2$ qubits that correct arbitrary t -qubit errors has been found [9]. Here, we extend the theory of permutation-invariant codes. Our permutation-invariant code \mathcal{C} has as its basis vectors the logical 1 of D distinct permutation invariant codes given by [9], where each such code encodes only a single qubit. Surprisingly, this simple construction can yield a permutation-invariant code encoding more than a single qubit while correcting spontaneous decay errors to leading order.

Permutation-invariant codes are particularly useful in correcting errors induced by *quantum permutation chan-*

nels with spontaneous decay errors, with Kraus decomposition $\mathcal{N}(\rho) = \mathcal{A}(\mathcal{P}(\rho)) = \sum_{\alpha, \beta} A_{\beta} P_{\alpha} \rho P_{\alpha}^{\dagger} A_{\beta}$, where \mathcal{P} and \mathcal{A} are quantum channels satisfying the completeness relation $\sum_{\alpha} P_{\alpha}^{\dagger} P_{\alpha} = \sum_{\beta} A_{\beta}^{\dagger} A_{\beta} = \mathbb{1}$ and $\mathbb{1}$ is the identity operator on m qubits. The channel \mathcal{P} has each of its Kraus operators P_{α} proportional to $e^{i\theta_{\alpha} \hat{a}_{\alpha}}$, where θ_{α} is the infinitesimal parameter and the infinitesimal generator \hat{a}_{α} is any linear combination of exchange operators. By a judicious choice of θ_{α} and \hat{a}_{α} , the channel \mathcal{P} can model the stochastic reordering and coherent exchange of quantum packets as well as out-of-order delivery of classical packets [10]. The channel \mathcal{A} on the other hand models spontaneous decay errors, otherwise also known as amplitude damping errors, where an excited state in each qubit independently relaxes to the ground state with probability γ . Our permutation-invariant code is inherently robust against the effects of channel \mathcal{P} , and can suppress all errors of order γ introduced by channel \mathcal{A} , and is hence approximately robust against the composite noisy permutation channel \mathcal{N} .

We quantify the error correction capabilities of our permutation-invariant codes \mathcal{C} with code projector Π beginning from the approximate quantum error correction criterion of Leung *et al.* [11]. Since the Kraus operators P_{α} of the permutation channel leave the codespace of any permutation-invariant code unchanged, it suffices only to consider the effects of the amplitude damping channel \mathcal{A} . The optimal entanglement fidelity between an adversarially chosen state ρ in the permutation-invariant codespace and error-corrected noisy counterpart is just

$$1 - \epsilon = \sup_{\mathcal{R}} \inf_{\rho} \mathcal{F}_e(\rho, \mathcal{R} \circ \mathcal{A}), \quad (1)$$

where ϵ is the *worst case error* [9] that we need to suppress. Lower bounds for the above quantity can be found using various techniques from the theory of optimal recovery channels [9, 12–17], but we restrict our attention to the simpler (but suboptimal) approach of [9, 11]. Suppose that we can find a truncated Kraus set Ω [18] of the channel \mathcal{A} such that for every distinct pair of $A, B \in \Omega$, the spaces AC and BC are pairwise orthogonal. Then the truncated recovery map of Leung

et al. $\mathcal{R}_{\Omega, \mathcal{C}}(\mu) := \sum_{A \in \Omega} \Pi U_A^\dagger \mu U_A \Pi$ is a valid quantum operation, where U_A is the unitary in the polar decomposition of $A\Pi = U_A \sqrt{\Pi A^\dagger A} \Pi$. Since $\mathcal{R}_{\Omega, \mathcal{C}}$ is now a special instance of a recovery channel in Eq. (1), we trivially get $\epsilon \leq 1 - \inf_\rho \mathcal{F}_e(\rho, \mathcal{R}_{\Omega, \mathcal{C}} \circ \mathcal{A})$. As explained in [9], the analysis of Leung *et al.* [11] allows one to show that

$$\mathcal{F}_e(\rho, \mathcal{R}_{\Omega, \mathcal{C}} \circ \mathcal{A}) \geq \sum_{A \in \Omega} \lambda_A, \quad (2)$$

where $\lambda_A = \min_{\langle \psi | \psi \rangle = 1} \langle \psi | A^\dagger A | \psi \rangle$ quantifies the worst case deformation of each corrupted codespace \mathcal{AC} .

The symmetric subspace of m qubits is central to the study of permutation-invariant codes, and has a convenient choice of basis vectors, namely the *Dicke states* [9, 19–21]. A Dicke state of weight w , denoted as $|D_w^m\rangle$, is a normalized permutation-invariant state on m qubits with a single excitation on w qubits. Our code \mathcal{C} is the span of the logical states $|d_L\rangle$ for $d = 1, \dots, D$, and these states can be written as superposition over Dicke states, with amplitudes proportional to the square root of the binomial distribution. Namely for positive integers n_d and g_d ,

$$|d_L\rangle = \sum_{j \in \mathcal{I}_d} \sqrt{\frac{\binom{n_d}{j}}{2^{n_d-1}}} |D_{g_d j}^m\rangle \quad (3)$$

and the set \mathcal{I}_d comprises of the odd integers from 1 to $2\lfloor \frac{n_d-1}{2} \rfloor + 1$. The states $|d_L\rangle, A|d_L\rangle$ can be made to be pairwise orthogonal via a judicious choice of constraints on the positive integer parameters $n_1, \dots, n_D, g_1, \dots, g_D$ and m .

We elucidate the case for $D \geq 3$ since permutation invariant codes encoding only one qubit [9] are already known. Here, we require n_1, \dots, n_D to be pairwise coprime integers with $n_1 \leq \dots \leq n_D$, and define their product to be $N = n_1 \dots n_D$. The length of our code is a polynomial in N , given by $m = N^q$ for any integer $q \geq 3$. Moreover we set $g_d = N/n_d$ so that for distinct d and d' , the greatest common divisor of g_d and $g_{d'}$ is precisely $\gcd(g_d, g_{d'}) = N/(n_d n_{d'}) > 1$, so that g_d and $g_{d'}$ are not coprime. Furthermore, we require that $g_d \geq 3, n_d \geq 4$.

The reason for requiring g_d and $g_{d'}$ to not be coprime is that it allows the inner products $\langle d_L | d'_L \rangle$ and $\langle d_L | A^\dagger B | d'_L \rangle$ to be identically zero for distinct d and d' and for any operators A, B acting nontrivially on strictly less than $\frac{\min_d g_d}{2}$ qubits when N is even. To see this, we analyze the linear Diophantine equation

$$x_{d,d'} g_d = y_{d,d'} g_{d'} + s, \quad (4)$$

with $s = 0, \pm 1$. This linear Diophantine equation has a solution $(x_{d,d'}, y_{d,d'})$ if and only if s is a multiple of $\gcd(g_d, g_{d'})$. Having $\gcd(g_d, g_{d'}) > 1$ ensures that Eq. (4) has no solution for non-zero s such that $|s| < \gcd(g_d, g_{d'})$. When $s = 0$, integer solutions $(x_{d,d'}, y_{d,d'})$ where $0 <$

$x_{d,d'} g_d = y_{d,d'} g_{d'} < N$ do not exist. To see this, note that the minimum positive solutions of Eq. (4) are precisely $x_{d,d'} = \frac{g_{d'}}{\gcd(g_d, g_{d'})}$ and $y_{d,d'} = \frac{g_d}{\gcd(g_d, g_{d'})}$, and hence we must require that $\frac{g_d g_{d'}}{\gcd(g_d, g_{d'})} < N$ be an invalid inequality. But our construction gives $\frac{g_d g_{d'}}{\gcd(g_d, g_{d'})} = \frac{g_d g_{d'} n_d n_{d'}}{N} = N$. This immediately implies several orthogonality conditions on the states given by Eq. (3) for large n_1 .

We use a sequence of large consecutive primes and an even number to construct our sequence of coprimes. We let $n_1 = p_k$, where p_k denotes the k -th prime, and let $n_2 = n_1 + 1$. We also let $n_j = p_{k+j-2}$ for all $j = 3, \dots, D$, which gives us our D coprime integers. The length of our code is $m = ((p_k + 1)(p_k \dots p_{k+D-2}))^q$. In the special case when $D = 3$, we can use the existence of twin primes n_1 and n_3 a bounded distance apart [22] (at most 600 apart [23]), and let $n_2 = n_1 + 1$, which yields $m = (n_1 n_3 (n_1 + 1))^q$.

The oft used Kraus operators for an amplitude damping channel on a single qubit are $A_0 = |0\rangle\langle 0| + \sqrt{1-\gamma}|1\rangle\langle 1|$ and $A_1 = \sqrt{\gamma}|0\rangle\langle 1|$ respectively, with γ modeling the probability for a transition from the excited $|1\rangle$ state to the ground state $|0\rangle$. On m qubits, the Kraus operators of the amplitude damping channel have a tensor product structure, given by $A_{x_1} \otimes \dots \otimes A_{x_m}$ where $x_1, \dots, x_m = 0, 1$. We focus our attention on the Kraus operators $K_0 = A_0^{\otimes m}$, and F_j which applies A_1 on the j -th qubit and applies A_0 everywhere else for $j = 1, \dots, m$. The choice of Kraus operators for a quantum channel is not unique, and we can equivalently consider a subset of the Kraus operators in a Fourier basis. Namely, for $\ell = 1, \dots, m$, we define $K_\ell = \frac{1}{\sqrt{m}} \sum_{j=1}^m \omega^{(\ell-1)(j-1)} F_j$, where $\omega = e^{2\pi i/m}$. We choose the set of Kraus operators that we wish to correct to be $\Omega = \{K_0, K_1, \dots, K_m\}$.

Now the spaces \mathcal{AC} and \mathcal{BC} are orthogonal for distinct $A, B \in \Omega$. Note that for $\ell, \ell' = 1, \dots, m$,

$$\begin{aligned} & \langle d_L | K_\ell^\dagger K_{\ell'} | d_L \rangle \\ &= \frac{1}{m} \sum_{j=1}^m \sum_{j'=1}^m \omega^{-(\ell-1)(j-1) + (\ell'-1)(j'-1)} \langle d_L | F_j^\dagger F_{j'} | d_L \rangle \\ &= \sum_{j=1}^m \omega^{(\ell'-\ell)(j-1)} \langle d_L | F_j^\dagger F_j | d_L \rangle \\ &+ \frac{1}{m} \sum_{d=1}^{m-1} \sum_{j=1}^m \omega^{-(\ell-1)(j-1) + (\ell'-1)(j-1+d)} \langle d_L | F_j^\dagger F_{j+d} | d_L \rangle, \end{aligned} \quad (5)$$

where the addition in the subscript is performed modulo m . Using the invariance of $\langle d_L | F_j^\dagger F_j | d_L \rangle$ and $\langle d_L | F_j^\dagger F_{j'} | d_L \rangle$ for distinct $j, j' = 1, \dots, m$ along with the identity

$$\sum_{d=1}^{m-1} \sum_{j=1}^m \omega^{-(\ell-1)(j-1) + (\ell'-1)(j-1+d)} = (m\delta_{\ell',1} - 1)m\delta_{\ell,\ell'},$$

one can simplify (5) to get

$$\begin{aligned} & \langle d_L | K_\ell^\dagger K_{\ell'} | d_L \rangle \\ &= \delta_{\ell, \ell'} \left(\langle d_L | F_1^\dagger F_1 | d_L \rangle + (m\delta_{\ell, 1} - 1) \langle d_L | F_1^\dagger F_m | d_L \rangle \right), \end{aligned} \quad (6)$$

which completes the proof of the orthogonality of AC and BC for distinct $A, B \in \Omega$.

Now we have

$$\begin{aligned} \langle d_L | K_0^\dagger K_0 | d_L \rangle &= \sum_{t \in \mathcal{I}_d} \frac{\binom{n_d}{t}}{2^{n_d-1}} (1 - \gamma)^{g_d t} \\ \langle d_L | F_1^\dagger F_1 | d_L \rangle &= \gamma \sum_{t \in \mathcal{I}_d} \frac{\binom{n_d}{t}}{2^{n_d-1}} (1 - \gamma)^{g_d t-1} \frac{g_d t}{m} \\ \langle d_L | F_1^\dagger F_m | d_L \rangle &= \gamma \sum_{t \in \mathcal{I}_d} \frac{\binom{n_d}{t}}{2^{n_d-1}} (1 - \gamma)^{g_d t-1} \frac{g_d t(m - g_d t)}{m(m-1)}. \end{aligned} \quad (7)$$

Using the Taylor series $(1 - \gamma)^{g_d t} = 1 - g_d t \gamma + \frac{g_d t(g_d t-1)}{2} \gamma^2 + O(\gamma^3)$ and $(1 - \gamma)^{g_d t-1} = 1 - (g_d t - 1)\gamma + O(\gamma^2)$ with the binomial identities $\sum_{t=0}^{n_d} t \binom{n_d}{t} = 2^{n_d-1} n_d$, $\sum_{t=0}^{n_d} t^2 \binom{n_d}{t} = 2^{n_d-2} n_d(n_d + 1)$ and $\sum_{t=0}^{n_d} t^3 \binom{n_d}{t} = 2^{n_d-3} n_d^2(n_d + 3)$ [9, 24], we get

$$\begin{aligned} \langle d_L | K_0^\dagger K_0 | d_L \rangle &= 1 - \frac{N}{2} \gamma \\ &\quad + \left(\frac{N^2 + N g_d}{8} - \frac{N}{4} \right) \gamma^2 + O(\gamma^3) \\ \langle d_L | F_1^\dagger F_1 | d_L \rangle &= \frac{N}{2m} \gamma - \left(\frac{N^2 + N g_d}{4m} - \frac{N}{2m} \right) \gamma^2 \\ &\quad + O(\gamma^3) \\ \langle d_L | F_1^\dagger F_m | d_L \rangle &= \frac{\left(\frac{N}{2} - \frac{N^2 + N g_d}{4m} \right)}{m-1} \gamma \\ &\quad + \frac{N^3 + 3N^2 g_d}{8m(m-1)} \gamma^2 \\ &\quad - \frac{(N^2 + N g_d) \left(1 + \frac{1}{m} \right) - 2N}{4(m-1)} \gamma^2 \\ &\quad + O(\gamma^3). \end{aligned} \quad (8)$$

Now for all $|\psi\rangle \in \mathcal{C}$ where $\langle \psi | \psi \rangle = 1$, we can write $|\psi\rangle = \sum_{d=1}^D a_d |d_L\rangle$ such that $\sum_{d=1}^D |a_d|^2 = 1 + O(2^{-n_1})$ [31]. Hence for all $A \in \Omega$, $\langle \psi | A^\dagger A | \psi \rangle = \sum_{d=1}^D |a_d|^2 \langle d_L | A^\dagger A | d_L \rangle$ which implies that $\lambda_A \geq \min_{d=1, \dots, D} \langle d_L | A^\dagger A | d_L \rangle (1 + O(2^{-n_1}))$. This implies that

$$1 - \epsilon \geq 1 - \frac{N g_1}{4m} \gamma - \frac{c N^2}{8} \gamma^2 + O(\gamma^3) + O(2^{-n_1}), \quad (9)$$

where

$$c = 1 + \frac{2g_D - g_1}{N} - \frac{2}{N} + \frac{3g_1}{m} + \frac{4g_1}{N}. \quad (10)$$

Since $m = N^q$, $1 - \epsilon \geq 1 - \frac{1}{4N^{q-2}} \gamma - \frac{c N^2}{8} \gamma^2 + O(\gamma^3) + O(2^{-n_1})$ and for fixed N and large q , the asymptotic error is second order in γ with $\epsilon \sim \frac{c' N^2}{8} \gamma^2 + O(\gamma^3) + O(2^{-n_1})$, where $c' = 1 + \frac{2g_D - g_1}{N} - \frac{2}{N} + \frac{4g_1}{N}$.

In summary, we have generalized the construction of permutation-invariant codes to enable the encoding of multiple qubits while suppressing leading order spontaneous decay errors. These permutation-invariant codes might allow for the construction of new schemes in physical systems, such as improved quantum communication along isotropic Heisenberg spin-chains [25–28]. Symmetry of error-correction codes have also recently been exploited to symmetrise prover strategies in the context of interactive proofs [29, 30], and so the extremely high symmetry of the codes studied here may also have theoretical implications.

This research was supported by the Singapore National Research Foundation under NRF Award No. NRF-NRFF2013-01. Y. Ouyang also acknowledges support from the Ministry of Education, Singapore.

* Electronic address: yingkai.ouyang@sutd.edu.sg

- [1] C. H. Bennett and G. Brassard, “Quantum cryptography: Public key distribution and coin tossing,” in *Proceedings of IEEE International Conference on Computers, Systems and Signal Processing*, vol. 175, New York, 1984.
- [2] A. K. Ekert, “Quantum cryptography based on Bell’s theorem,” *Phys. Rev. Lett.*, vol. 67, pp. 661–663, Aug 1991.
- [3] M. A. Nielsen and I. L. Chuang, *Quantum Computation and Quantum Information*. Cambridge University Press, second ed., 2000.
- [4] P. Zanardi and M. Rasetti, “Noiseless Quantum Codes,” *Phys. Rev. Lett.*, vol. 79, pp. 3306–3309, Oct. 1997.
- [5] S. Blundell, *Magnetism in Condensed Matter*. Great Clarendon Street, Oxford OX2 6DP: Oxford master series in condensed matter physics, first rnote ed., 2003.
- [6] D. A. Lidar, D. Bacon, and K. B. Whaley, “Concatenating decoherence-free subspaces with quantum error correcting codes,” *Phys. Rev. Lett.*, vol. 82, pp. 4556–4559, May 1999.
- [7] M. B. Ruskai, “Pauli Exchange Errors in Quantum Computation,” *Phys. Rev. Lett.*, vol. 85, pp. 194–197, July 2000.
- [8] H. Pollatsek and M. B. Ruskai, “Permutationally invariant codes for quantum error correction,” *Linear Algebra and its Applications*, vol. 392, no. 0, pp. 255–288, 2004.
- [9] Y. Ouyang, “Permutation-invariant quantum codes,” *Physical Review A*, vol. 90, no. 6, p. 062317, 2014.
- [10] V. Paxson, “End-to-end internet packet dynamics,” *SIGCOMM Comput. Commun. Rev.*, vol. 27, pp. 139–152, Oct. 1997.
- [11] D. W. Leung, M. A. Nielsen, I. L. Chuang, and Y. Yamamoto, “Approximate quantum error correction can lead to better codes,” *Phys. Rev. A*, vol. 56, p. 2567, 1997.
- [12] H. Barnum and E. Knill, “Reversing quantum dynamics

- with near-optimal quantum and classical fidelity,” *Journal of Mathematical Physics*, vol. 43, p. 2097, Jan. 2002.
- [13] A. S. Fletcher, P. W. Shor, and M. Z. Win, “Channel-Adapted Quantum Error Correction for the Amplitude Damping Channel,” *IEEE Transactions on Information Theory*, vol. 54, pp. 5705–5718, Dec. 2008.
- [14] N. Yamamoto, “Exact solution for the max-min quantum error recovery problem,” in *Decision and Control, 2009 held jointly with the 2009 28th Chinese Control Conference. CDC/CCC 2009. Proceedings of the 48th IEEE Conference on*, pp. 1433–1438, IEEE, Dec. 2009.
- [15] J. Tyson, “Two-sided bounds on minimum-error quantum measurement, on the reversibility of quantum dynamics, and on maximum overlap using directional iterates,” *Journal of Mathematical Physics*, vol. 51, p. 92204, June 2010.
- [16] C. Bény and O. Oreshkov, “General Conditions for Approximate Quantum Error Correction and Near-Optimal Recovery Channels,” *Phys. Rev. Lett.*, vol. 104, p. 120501, Mar. 2010.
- [17] C. Bény and O. Oreshkov, “Approximate simulation of quantum channels,” *Phys. Rev. A*, vol. 84, p. 022333, Aug. 2011.
- [18] Y. Ouyang and W. H. Ng, “Truncated quantum channel representations for coupled harmonic oscillators,” *Journal of Physics A: Mathematical and Theoretical*, vol. 46, no. 20, p. 205301, 2013.
- [19] M. Bergmann and O. Gühne, “Entanglement criteria for Dicke states,” *Journal of Physics A: Mathematical and Theoretical*, vol. 46, no. 38, p. 385304, 2013.
- [20] T. Moroder, P. Hyllus, G. Tóth, C. Schwemmer, A. Niggebaum, S. Gaile, O. Gühne, and H. Weinfurter, “Permutationally invariant state reconstruction,” *New Journal of Physics*, vol. 14, no. 10, p. 105001, 2012.
- [21] G. Tóth and O. Gühne, “Entanglement and Permutational Symmetry,” *Phys. Rev. Lett.*, vol. 102, p. 170503, May 2009.
- [22] Y. Zhang, “Bounded gaps between primes,” *Annals of Mathematics*, vol. 179, no. 3, pp. 1121–1174, 2014.
- [23] J. Maynard, “Small gaps between primes,” *arXiv preprint arXiv:1311.4600*, 2013.
- [24] A. Prudnikov, Y. A. Brychkov, and O. Marichev, *Integrals and Series, Volume 1, Elementary Functions*. Gordon and Breach, 1986.
- [25] D. Burgarth and S. Bose, “Conclusive and arbitrarily perfect quantum-state transfer using parallel spin-chain channels,” *Phys. Rev. A*, vol. 71, p. 052315, May 2005.
- [26] D. Burgarth, V. Giovannetti, and S. Bose, “Efficient and perfect state transfer in quantum chains,” *Journal of Physics A: Mathematical and General*, vol. 38, no. 30, p. 6793, 2005.
- [27] D. Burgarth and S. Bose, “Perfect quantum state transfer with randomly coupled quantum chains,” *New Journal of Physics*, vol. 7, no. 1, p. 135, 2005.
- [28] K. Shizume, K. Jacobs, D. Burgarth, and S. Bose, “Quantum communication via a continuously monitored dual spin chain,” *Phys. Rev. A*, vol. 75, p. 062328, Jun 2007.
- [29] J. Fitzsimons and T. Vidick, “A multiprover interactive proof system for the local hamiltonian problem,” in *Proceedings of the 2015 Conference on Innovations in Theoretical Computer Science*, pp. 103–112, ACM, 2015.
- [30] Z. Ji, “Classical verification of quantum proofs,” *arXiv preprint arXiv:1505.07432*, 2015.
- [31] The term $O(2^{-n_1})$ arises because of the slight non-orthogonality of the states $|d_L\rangle$.